



Brightness+/- press the button, can adjust the brightness 10%~100%

Color Temperature+/- press the button, can adjust the color temperature 3000K~6500K

Memory press the button more than 3s, can “remember” the current brightness and color temperature;next time you press the button, will change back into the remembered brightness and color temperature

WW\NW\CW press the button, can change the color temperature,only 3 type, WW\NW\CW

Moonlight press the button, change into moonlight model

Group A\B\C press the button, can control the lamps of one group together

All On/Off press the button, can control the lamps of all group together

Operation

First of all, match the lamp and remote control

1. You can match one lamp and remote control

Step a: keep the lamp turn off

Step b: press the button A(or B or C), when the indicator light on remote control light on, turn on the lamp. Pls note that must keep press the button A(or B or C) all the time.

Step c: still keep press the button A(or B or C), until the lamp flicker, which means the lamp and remote control match successfully. If the lamp doesn't flicker, repeat the step a,b,c.

After match the lamp successfully, you can use the remote control to control the lamp

2. You can also match several lamps as a group

Step a: keep the lamps turn off

Step b: press the button A(or B or C), when the indicator light on remote control light on, turn on the lamps **together**.

Step c: still keep press the button A(or B or C), until the lamps flicker. If the lamps don't flicker, repeat the step a,b,c

After match the lamps successfully, you can use the remote control to control the lamps of one group together.

PS. The max for one group is 15pcs lamp

How to switch in different group?

Step 1. Match lamps to group A, then match other lamps to group B, group C in the same way.

Step 2. Press button A(or B or C), all the lamps of group A(or B or C) will turn off.

Step 3. Press button A(or B or C) again, all the lamps of group A (or B or C) will turn on.

Step 4. Now group A(or B or C) is under control, you can adjust the color temperature and brightness of group A(or B or C).

How to control 3 groups together?

Step 1. Match lamps to group A, then match other lamps to group B, group C in the same way.

Step 2. Press button ALL OFF, all the lamps of 3 groups will turn off.

Step 3. Then press button ALL ON, all the lamps of 3 groups will turn on.

Step 4. Now all the 3 groups are under control together, you can adjust the color temperature and brightness of 3 groups.